

KEL 8800 Series Mating Matrix

(20, 26, 28, 30, 32, 34, 36, 40, 50, 52, 60, 68, 80, 100, 120, 140, 160, 180 and 200 positions)

RECEPTACLE CONNECTORS											
8810-□□□-170S□-F 8810-□□□-170□-F	8801-□□□-170S□-F 8801-□□□-170□-F	8802-□□□-170S□-F 8802-□□□-170□-F	8803-□□□-170S□-F 8803-□□□-170□-F	8822-□□□-171□-F	8822E-□□□-171□-F	8825E-□□□-175□-F	8806-□□□-170S□-F 8806-□□□-170□-F	8807-□□□-170S□-F 8807-□□□-170□-F	880□S-□□□-170S□-F 880□S-□□□-170□-F	8840-□□□-174□-F	
*1 ○	*1 ○	*1 ○	*1 ○	No	No	No	No	No	No	No	
*1 ○	*1 ○	*1 ○	No	No	No	No	No	No	No	No	
*1 ○	*1 ○	*1 ○	No	*2 ○	No	No	No	No	No	No	
No	No	*1 ○	*1 ○	No	No	No	No	No	No	No	
*2 ○	*2 ○	*2 ○	No	*2 ○	No	No	No	No	No	No	
*2 ○	*2 ○	*2 ○	No	*2 ○	No	No	No	No	No	No	
*1 ○	*1 ○	*1 ○	No	No	*3 ○	*1 ○	No	No	No	No	
*1 ○	*1 ○	*1 ○	No	No	*3 ○	*1 ○	No	No	No	No	
*4 ○	*4 ○	*4 ○	No	No	No	No	No	No	No	No	
No	No	No	No	No	No	No	No	*5 ○	No	No	
No	No	No	No	No	No	No	No	*5 ○	No	No	
No	No	No	No	No	No	No	No	No	*6 ○	No	
No	No	No	No	No	No	No	No	No	No	*7 ○	
No	No	No	No	No	No	No	No	No	No	*7 ○	

PLUG CONNECTORS

- *1 :20, 26, 30, 32, 34, 40, 50, 52, 60, 68, 80 and 100 positions are available
- *2 :20, 26, 30, 32, 34, 40, 50, 52, 60 and 68 positions are available
- *3 :20, 26, 30, 32, 34, 36, 40, 50, 52, 60, 68, 80 and 100 positions are available
- *4 :20, 30, 40, 50, 60, 80 and 100 positions are available
- *5 :120, 140, 160, 180 and 200 positions are available
- *6 :40 and 50 positions are available
- *7 :20, 28, 34, 50, 60, 68, 80 and 100 positions are available